

## SV1813DAWPZ

### Cordless Random Orbital Sander

18V - 11,000 RPM

0000000000000

Compatible with  
**BRUSHLESS**

**NEW**

11,000 RPM random orbital movement

High dust collecting efficiency

Speed adjustment dial

Low vibration and lightweight



#### Specifications

Voltage	18V
No-load speed	7,000 - 11,000 RPM
Orbital diameter	3.0 mm
Pad size diameter	125 mm
Motor type	Brushless
Variable speed setting	Yes
Soft start	Yes
Brake	Yes
Dimensions (L x W x H)	158 x 158 x 153 mm
Weight <sup>1</sup>	1.8 kg

#### Characteristics

High 11,000 RPM random orbital movement for fast and consistent sanding of even large surfaces

Easily accessible variable speed dial for setting the right speed for each material

Includes easy to empty dustbag for dust free working without vacuum cleaner

Low tool vibration for comfortable working and clean surfaces

Low tool weight for fatigue-free working

Efficient dust collection rate: connectable to vacuum cleaner or dust bag for dust-free working environment and high user protection

#### Standard accessories<sup>2</sup>

2x battery BSL1850C
Charger UC18YFSL
Dust bag
2x dust extraction adapter
Sanding pad
2x sanding paper (120)
Stackable case HSC II

#### Further versions

<b>SV1813DAW2Z:</b>	Dust bag, 2x dust extraction adapter, sanding pad, 2x sanding paper (120). In stackable case HSC II
<b>SV1813DAW4Z:</b>	Dust bag, 2x dust extraction adapter, sanding pad, 2x sanding paper (120). In cardboard box

<sup>1</sup> Weight according to EPTA-2004 procedure.

<sup>2</sup> Standard accessories vary by country or area.

Read everything  
about our services at  
[hikoki-powertools.com](http://hikoki-powertools.com)

